

## Escape Sequences for Epson Printers

File these instructions in the MACS Software User's Manual

### Requirements

Operating System: Any  
MACS Version: 5.0 or higher

### Situation

User needs the escape sequences for Epson printers. In all the following cases, **OPTION 5 PRINTER INITIALIZATION STRING REQUIRED** should be set to (1) **YES**. If a Termination String is specified below, **OPTION 6** should also be set to (1) **YES**, otherwise it should be set to (2) **NO**.

For complete instructions, refer to Support Memo 104.

### Solution

1. Set printer for condensed mode  
**INITIALIZATION STRING:** 1B 0F  
**TERMINATION STRING:** 1B 40
  
2. Set printer for 12 cpi  
**INITIALIZATION STRING:** 1B 4D
  
3. Set printer for 12 cpi, force draft quality  
**INITIALIZATION STRING:** 1B 78 00 1B 4D
  
4. Set printer for 12 cpi, force letter quality  
**INITIALIZATION STRING:** 1B 78 01 1B 4D
  
5. Set printer for 10 cpi  
**INITIALIZATION STRING:** 1B 50
  
6. Set printer for 10 cpi, force draft quality  
**INITIALIZATION STRING:** 1B 78 00 1B 50
  
7. Set printer for 10 cpi, force letter quality  
**INITIALIZATION STRING:** 1B 78 01 1B 50
  
8. Set printer for 10 cpi, 51 lines per page  
**INITIALIZATION STRING:** 1B 50 1B 43 51  
**TERMINATION STRING:** 1B 40